

# AERIAL DIMENSION CHART

## AMATEUR RADIO ANTENNA LENGTH CHART

	FREQUENCY (Mhz)	1/4λ (Feet)	1/2λ (Feet)	1λ (Feet)	1/2λ Inv Vee 90° (Feet)
<b>160</b> METERS	1.800	130' 0"	260' 0"	558' 4"	257' 5"
	1.850	126' 6"	253' 0"	543' 3"	250' 5"
	1.900	123' 2"	246' 4"	528' 11"	243' 10"
	2.000	117' 0"	234' 0"	502' 6"	231' 8"
<b>80</b> METERS	3.500	66' 10"	133' 9"	287' 2"	132' 5"
	3.750	62' 5"	124' 10"	268' 0"	123' 7"
	3.900	60' 0"	120' 0"	257' 8"	118' 10"
	4.000	58' 6"	117' 0"	251' 3"	115' 10"
<b>40</b> METERS	7.000	33' 5"	66' 10"	143' 7"	66' 2"
	7.150	32' 9"	65' 5"	140' 7"	64' 10"
	7.300	32' 1"	64' 1"	137' 8"	63' 6"
<b>30</b> METERS	10.100	23' 2"	46' 4"	99' 6"	45' 10"
	10.150	23' 1"	46' 1"	99' 0"	45' 8"
<b>20</b> METERS	14.000	16' 9"	33' 5"	71' 9"	33' 1"
	14.150	16' 6"	33' 1"	71' 0"	32' 9"
	14.300	16' 4"	32' 9"	70' 3"	32' 5"
	14.350	16' 4"	32' 7"	70' 0"	32' 3"
<b>17</b> METERS	18.068	12' 11"	25' 11"	55' 7"	25' 8"
	18.168	12' 11"	25' 9"	55' 4"	25' 6"
<b>15</b> METERS	21.000	11' 2"	22' 3"	47' 10"	22' 1"
	21.200	11' 0"	22' 1"	47' 5"	21' 10"
	21.450	10' 11"	21' 10"	46' 10"	21' 7"
<b>12</b> METERS	24.890	9' 5"	18' 10"	40' 5"	18' 7"
	24.990	9' 4"	18' 9"	40' 3"	18' 6"
<b>10</b> METERS	28.000	8' 4"	16' 9"	35' 11"	16' 7"
	28.500	8' 3"	16' 5"	35' 3"	16' 3"
	29.700	7' 11"	15' 9"	33' 10"	15' 7"
<b>6</b> METERS	50.000	4' 8"	9' 4"	20' 1"	9' 3"
	54.000	4' 4"	8' 8"	18' 7"	8' 7"
<b>2</b> METERS	144.000	1' 8"	3' 3"	7' 0"	3' 3"
	148.000	1' 7"	3' 2"	6' 9"	3' 2"

Antenna length calculations are based on the following formulas:  
 1/2 wave dipole (feet) = 468/frequency in Mhz  
 Full wave loop (feet) = 1005/frequency in Mhz  
 Inverted Vee with 90 degree included angle is 99% the length of 1/2 wave dipole

Note:  
 Cut wire slightly longer to allow for connecting insulators and pruning.  
 Height above ground, nearby wires, trees, etc. will change tuning slightly.

MILLENNIA  
ARTS

**NOTE:**  
 ALL MEASUREMENTS ON THE CHART IS PER LEG